

MONITORS QUIZ

1. Set up Mackie 24x4 or 32x4 mixer
2. Set up Mackie speakers as main speakers
3. Set up JBL wedges (all 4 speakers on floor) in standard monitor configuration
 - a. Use both Crown amps to establish 4 individual channels
 - b. Plug into snake to sync with the four 1/4" aux sends on the board
 - c. Demonstrate proper wedge placement to cardioid and supercardioid mics
4. Make the following connections directly to mixer
 - a. Channel 1: vocal mic (male voice)
 - b. Channel 2: vocal mic (female voice)
 - c. iPod
5. Set up the following:
 - a. Talk back mic
6. Power up equipment
7. Set levels at board and amps properly (use iPod mix as your level check)
 - a. Demonstrate solo function for aux sends
8. Send all signals to main speakers
9. Set the following mix:
 - a. Weak MALE vocals in monitors 1 and 3, strong MALE vocals to monitors 2 and 4
 - b. Strong FEMALE vocals in monitors 1 and 3, weak FEMALE vocals to monitors 2 and 4
 - c. Strong then weak overall monitor volume
 - d. Talk back mic sent ONLY to monitors
 - e. Adjust settings to send more MALE vocals to monitor 1, less FEMALE vocals in monitor 3, and iPod mix to monitors 2 and 4 only
10. Power down
11. Zero mixer
12. Undo all connections